



98W11 RS232 Codes

3 Bytes Cmd List

POWER_Off	69	76	20
POWER_On	69	53	43
ENTER	69	07	8F
MUTE	69	37	5F
1	79	85	01
2	79	84	02
3	79	83	03
4	79	82	04
5	79	81	05
6	79	80	06
7	79	7F	07
8	79	7E	08
9	79	7D	09
0	79	86	00
VOL+	79	41	45
VOL-	79	42	44
CH+	79	10	76
CH-	79	11	75
SOURCE	69	19	7D
MENU	69	80	16
LEFT	69	63	33
RIGHT	69	66	30
DOWN	69	43	53
UP	69	46	50
Screen Size	79	13	73
Picture Mode	79	14	72
Sound Mode	79	15	71
Sleep Timer	79	16	70
Blank	79	45	41
Get Power ON/OFF status	79	33	53
Get Power Save Mode	79	30	56
Get Panel Serial No	79	26	60

...continued over ->

3 Bytes Cmd List (Continued)

Get Mute ON/OFF status	79	44	42
Get Volume status	79	43	43
Get OPS Installed (Yes/No)	79	31	55
OPS On/Shutdown	79	32	54
Get Display Mode	79	25	61
Get Contrast	79	21	65
Get Brightness	79	20	66
Get Sharpness	79	22	64
Get Color Temp	79	23	63

Second Version 4 Bytes Cmd List

AV	89	55	0D	14
YPbPr	89	55	04	1D
VGA	89	65	03	0E
HDMI	89	65	0E	03
HDMI1	89	65	05	0C
HDMI2	89	65	07	0A
HDMI3	89	65	09	08
HDMI4	89	65	0B	06
OPS	89	65	0D	04
Back to Android	89	65	06	0B
Exit Android	89	15	53	0E
FREEZE	89	55	06	1B

For more information contact: info@activ2touch.com.au

©Activ2Touch. All rights reserved. Activ2Touch is a registered trademark of Activ2Touch in Australia and other countries. All trademarks are used with permission or are for identification purposes only and are the property of their respective companies.