



XX-W21K-U RS232 Codes

#	Set Function	Code HEX	Hex ID=1									ASCII ID=01
1	HDTV Power STBY	41(A)	6B	30	31	73	41	30	30	30	0D	k01sA000<CR>
2	HDTV Power ON	41(A)	6B	30	31	73	41	30	30	31	0D	k01sA001<CR>
3	Input Select : ATV	42(B)	6B	30	31	73	42	30	30	30	0D	k01sB000<CR>
4	Input Select : DTV	42(B)	6B	30	31	73	42	30	31	30	0D	k01sB010<CR>
5	Input Select : AV	42(B)	6B	30	31	73	42	30	30	31	0D	k01sB001<CR>
6	Input Select : YPbPr	42(B)	6B	30	31	73	42	30	30	33	0D	k01sB003<CR>
7	Input Select : HDMI	42(B)	6B	30	31	73	42	30	30	34	0D	k01sB004<CR>
8	Input Select : HDMI1	42(B)	6B	30	31	73	42	30	31	34	0D	k01sB014<CR>
9	Input Select : HDMI2	42(B)	6B	30	31	73	42	30	32	34	0D	k01sB024<CR>
10	Input Select : VGA	42(B)	6B	30	31	73	42	30	30	36	0D	k01sB006<CR>
11	Input Select : OPS1	42(B)	6B	30	31	73	42	30	30	37	0D	k01sB007<CR>
12	Input Select : DP	42(B)	6B	30	31	73	42	30	30	39	0D	k01sB009<CR>
13	Input Select : Launcher/Main (Android)	42(B)	6B	30	31	73	42	30	30	41	0D	k01sB00A<CR>
14	Contrast	43(C)	6B	30	31	73	43	3x	3x	3x	0D	k01sCxxx<CR>
15	Brightness	44(D)	6B	30	31	73	44	3x	3x	3x	0D	k01sDxxx<CR>
16	Sharpness	45(E)	6B	30	31	73	45	3x	3x	3x	0D	k01sExxx<CR>
17	Saturation	46(F)	6B	30	31	73	46	3x	3x	3x	0D	k01sFxxx<CR>
18	Hue	47(G)	6B	30	31	73	47	3x	3x	3x	0D	k01sGxxx<CR>
19	Color Mode : NORMAL	48(H)	6B	30	31	73	48	30	30	30	0D	k01sH000<CR>
20	Color Mode : WARM	48(H)	6B	30	31	73	48	30	30	31	0D	k01sH001<CR>
21	Color Mode : COLD	48(H)	6B	30	31	73	48	30	30	32	0D	k01sH002<CR>
22	Color Mode : USER	48(H)	6B	30	31	73	48	30	30	33	0D	k01sH003<CR>
23	Surround : SRS OFF	49(I)	6B	30	31	73	49	30	30	30	0D	k01sI000<CR>
24	Surround : SRS ON	49(I)	6B	30	31	73	49	30	30	31	0D	k01sI001<CR>
25	Bass	4A(J)	6B	30	31	73	4A	3x	3x	3x	0D	k01sJxxx<CR>
26	Treble	4B(K)	6B	30	31	73	4B	3x	3x	3x	0D	k01sKxxx<CR>
27	Picture Size: Full(16:9)	4D(M)	6B	30	31	73	4D	30	30	30	0D	k01sM000<CR>
28	Picture Size: Normal(4:3)	4D(M)	6B	30	31	73	4D	30	30	31	0D	k01sM001<CR>
29	Picture Size: AUTO	4D(M)	6B	30	31	73	4D	30	30	32	0D	k01sM002<CR>
30	Picture Size: PANORAMA	4D(M)	6B	30	31	73	4D	30	30	33	0D	k01sM003<CR>
31	Picture Size: Real (Just scan or PC)	4D(M)	6B	30	31	73	4D	30	30	34	0D	k01sM004<CR>
32	OSD Language : English	4E(N)	6B	30	31	73	4E	30	30	30	0D	k01sN000<CR>
33	OSD Language : French	4E(N)	6B	30	31	73	4E	30	30	31	0D	k01sN001<CR>

...continued over ->

#	Set Function	Code HEX	Hex ID=1									ASCII ID=01
34	OSD Language : Spanish	4E(N)	6B	30	31	73	4E	30	30	32	0D	k01sN002<CR>
35	OSD Language : Traditional Chinese	4E(N)	6B	30	31	73	4E	30	30	33	0D	k01sN003<CR>
36	OSD Language : Simple Chinese	4E(N)	6B	30	31	73	4E	30	30	34	0D	k01sN004<CR>
37	Volume	50(P)	6B	30	31	73	50	3x	3x	3x	0D	k01sPxxx<CR>
38	Volume: Down (-1)	50(P)	6B	30	31	73	50	32	30	30	0D	k01sP200<CR>
39	Volume: Up (+1)	50(P)	6B	30	31	73	50	32	30	31	0D	k01sP201<CR>
40	Mute : OFF	51(Q)	6B	30	31	73	51	30	30	30	0D	k01sQ000<CR>
41	Mute : ON(mute)	51(Q)	6B	30	31	73	51	30	30	31	0D	k01sQ001<CR>
42	Button Lock : Unlock	52(R)	6B	30	31	73	52	30	30	30	0D	k01sR000<CR>
43	Button Lock : Lock	52(R)	6B	30	31	73	52	30	30	31	0D	k01sR001<CR>
44	Menu Lock : Unlock	53(S)	6B	30	31	73	53	30	30	30	0D	k01sS000<CR>
45	Menu Lock : Lock	53(S)	6B	30	31	73	53	30	30	31	0D	k01sS001<CR>
46	Number (0~9)	54(T)	6B	30	31	73	54	3x	3x	3x	0D	k01sTxxx<CR>
47	Key Pad : UP	55(U)	6B	30	31	73	55	30	30	30	0D	k01sU000<CR>
48	Key Pad : DOWN	55(U)	6B	30	31	73	55	30	30	31	0D	k01sU001<CR>
49	Key Pad : LEFT	55(U)	6B	30	31	73	55	30	30	32	0D	k01sU002<CR>
50	Key Pad : RIGHT	55(U)	6B	30	31	73	55	30	30	33	0D	k01sU003<CR>
51	Key Pad : ENTER	55(U)	6B	30	31	73	55	30	30	34	0D	k01sU004<CR>
52	Key Pad : INPUT	55(U)	6B	30	31	73	55	30	30	35	0D	k01sU005<CR>
53	Key Pad : MENU	55(U)	6B	30	31	73	55	30	30	36	0D	k01sU006<CR>
54	Key Pad : EXIT	55(U)	6B	30	31	73	55	30	30	37	0D	k01sU007<CR>

Use the following settings:

Baud rate: 38400

For more information contact: info@azt.io

©A2T. All rights reserved. A2T is a registered trademark of A2T in Australia and other countries. All trademarks are used with permission or are for identification purposes only and are the property of their respective companies.

22/1/2021