



U-Series RS232 Codes

A2T-XX08-AD-10U

POWER_Off	69	76	20
POWER_On	69	53	43
ENTER	69	07	8F
MUTE	69	37	5F
1	69	92	04
2	69	A2	F4
3	69	B2	E4
4	69	93	03
5	69	A3	F3
6	69	B3	E3
7	69	94	02
8	69	A4	F2
9	69	B4	E2
0	69	95	01
VOL+	69	82	14
VOL-	69	85	11
CH+	69	C4	D2
CH-	69	C5	D1
SOURCE	69	19	7D
MENU	69	80	16
LEFT	69	63	33
RIGHT	69	66	30
DOWN	69	43	53
UP	69	46	50
LAN	69	34	62

...continued over ->

AV1	89	55	0D	14
AV2	89	55	12	0F
AV3	89	55	0A	17
AV4	89	55	15	0C
SV	89	55	19	08
YCbCr	89	55	04	1D
VGA	89	65	03	0E
HDMI1	89	65	05	0C
DVI	89	65	07	0A
HDMI2	89	65	07	0A
HDMI2	89	65	07	0A
FREEZE	89	55	06	1B
HDMI3	89	65	09	08
HDMI4	89	65	0B	06
OPS	89	65	0D	04
HDMI	89	65	0E	03

Use the following settings:

Baud rate: 38400

Data bit: 8

Stop bit: 1

Check bit: (Number)

For more information contact: info@activ2touch.com.au

©Activ2Touch. All rights reserved. Activ2Touch is a registered trademark of Activ2Touch in Australia and other countries. All trademarks are used with permission or are for identification purposes only and are the property of their respective companies.

17/4/2018