



P-Series RS232 Codes

A2T-XX06-AD-10P

POWER_Off	69	76	20
POWER_On	69	53	43
ENTER	69	7	8F
MUTE	69	37	5F
VOL+	69	82	14
VOL-	69	85	11
SOURCE	69	19	7D
MENU	69	80	16
LEFT	69	63	33
RIGHT	69	66	30
DOWN	69	43	53
UP	69	46	50
LAN	69	34	62

AV1	89	55	0D	14
YCbCr	89	55	4	1D
VGA	89	65	3	0E
HDMI1	89	65	5	0C
HDMI2	89	65	7	0A
FREEZE	89	55	6	1B
HDMI3	89	65	9	8
HDMI4	89	65	0B	6
OPS	89	65	0D	4
HDMI	89	65	0E	3

For more information contact: info@activ2touch.com.au

©Activ2Touch. All rights reserved. Activ2Touch is a registered trademark of Activ2Touch in Australia and other countries. All trademarks are used with permission or are for identification purposes only and are the property of their respective companies.

31/7/2016